

## Androtec Receiver MTR-90R Digital

### Laser receiver with mm display for rotating lasers with red/infrared laser light

Product number :27406000



#### Topfeatures

- Receiver with mm display
- Interference and flash filters
- For all common rotating lasers with red or infrared laser
- For all common rotating lasers with 300UpM to 1200UpM

#### All special features at a glance

- Compact receiver with mm display for all common rotating lasers
- The MTR-90 shows the deviation of the laser beam from the marking plane with an arrow symbol and digital numerical display accurate to the millimetre

#### Description

The ANDROTEC MTR-90R Digital Handheld Receiver is suitable for all common rotating lasers with red or infrared laser light. The receiver displays the deviation of the laser beam from the marking plane with millimetre accuracy. This enables quick measurement and correction of height differences. High-contrast displays on the front and back ensure that the measured values can be read quickly. With only one type AA battery, an operating time of over 45 hours is achieved.

#### Technical Details

Operating temperature	-20°C to +50 °C
Reception display	Display, sound signal, mm display
Detection range	90 mm / 80 mm numerical
Weight (without retaining clip)	0.2 with battery kg
Dimensions	135 x 69 x 25 mm
Precision levels	5 levels: 0.5 / 1 / 2 / 5 / 10 mm
Reach	400 m radius m
Protection class	IP67
Power supply	1 x AA battery

#### Scope of supply

Receiver, Retaining clip, 1 x AA battery